
The publications listed below form a part of this specification to the extent referenced. The publications are referred to within the text by the basic designation only.

AMERICAN NATIONAL STANDARDS INSTITUTE (ANSI)

ANSI C29.1 (1988; R 1996) Electrical Power Insulators
- Test Methods

NATIONAL ELECTRICAL MANUFACTURERS ASSOCIATION (NEMA)

NEMA SG 6 (2000) Power Switching Equipment

1.2 SUBMITTALS

NOTE: Review Submittal Description (SD) definitions in Section 01330 SUBMITTAL PROCEDURES and edit the following list to reflect only the submittals required for the project. Submittals should be kept to the minimum required for adequate quality control.

A "G" following a submittal item indicates that the submittal requires Government approval. Some submittals are already marked with a "G". Only delete an existing "G" if the submittal item is not complex and can be reviewed through the Contractor's Quality Control system. Only add a "G" if the submittal is sufficiently important or complex in context of the project.

For submittals requiring Government approval on Army projects, a code of up to three characters within the submittal tags may be used following the "G" designation to indicate the approving authority. Codes for Army projects using the Resident Management System (RMS) are: "AE" for Architect-Engineer; "DO" for District Office (Engineering Division or other organization in the District Office); "AO" for Area Office; "RO" for Resident Office; and "PO" for Project Office. Codes following the "G" typically are not used for Navy, Air Force, and NASA projects.

Choose the first bracketed item for Navy, Air Force and NASA projects, or choose the second bracketed item for Army projects.

Government approval is required for submittals with a "G" designation; submittals not having a "G" designation are [for Contractor Quality Control approval.] [for information only. When used, a designation following the "G" designation identifies the office that will review the submittal for the Government.] Submit the following in accordance with Section 01330 SUBMITTAL PROCEDURES:

SD-02 Shop Drawings

Fabrication Drawings shall be submitted in accordance with paragraph entitled, "General Requirements," of this section.

Installation Drawings shall be submitted for load-break switches in accordance with the paragraph entitled, "Installation," of this section.

SD-03 Product Data

Equipment and performance data shall be submitted for Load-Break Switches including life, test, system functional flows, safety features, and mechanical automated details.

Manufacturer's catalog data shall be submitted for the following items:

Load-Break Switches
Handles

SD-08 Manufacturer's Instructions

Manufacturer's instructions shall be submitted for Load-Break Switches including special provisions required to install equipment components and system packages. Special notices shall detail impedances, hazards and safety precautions.

SD-10 Operation and Maintenance Data

Operation and Maintenance Manuals shall be submitted for the following equipment:

Load Break Switches

1.3 GENERAL REQUIREMENTS

NOTE: If Section 16003S GENERAL ELECTRICAL PROVISIONS is not included in the project specification, applicable requirements therefrom should be inserted and the following paragraph deleted.

Section 16003S GENERAL ELECTRICAL PROVISIONS applies to work specified in this section.

Fabrication Drawings shall be submitted for load-break switches consisting of fabrication and assembly details to be performed in the factory.

PART 2 PRODUCTS

2.1 SWITCHES

Load-break switches shall be gang-operated, air-break, 3-insulator, 3-pole, single-throw, horizontal-mounted, vertical-break, rotating-insulator type for poletop or structure mounting suitable for the intended application.

Insulators and other component parts shall be in accordance with NEMA SG 6

and ANSI C29.1, except that the leakage distance of each insulator assembly shall be at least 600 millimeter 24 inches.

Switch rating shall not be less than 400 amperes.

Operating parts of switch assemblies shall be corrosion-resistant metals.

Switches shall be provided with suitable attachments to permit closing and opening under full rated load current without damage.

2.2 HANDLES

Operating handles shall be located approximately 1500 millimeter 5-feet above the ground and shall be provided with suitable attachments for padlocking the switches in both open and closed positions.

PART 3 EXECUTION

3.1 INSTALLATION

Switches shall be mounted in accordance with the manufacturer's instructions. Installation shall include necessary timbers, hardware, insulators, and connections to line wire or bus.

Prior to final acceptance the switch shall be energized and the circuit loaded (to the maximum load possible, but not less than 10 percent of expected full load) for a minimum of 10 minutes and the temperature measured, with a non-contact device, to verify contact pressure and alignment. The temperature detector shall be accurate within 0.5 degrees C. Each phase temperature shall be less than 5 degrees C above ambient and within 3 C degrees of each other. Temperatures outside these values warrant investigation.

Installation Drawings shall be submitted for load-break switches.

3.2 GROUNDING

NOTE: In locations where existing underground
utilities, equipment or structures may be damaged,
ground rod installation should be accomplished using
the water jetting method.

Ground rods shall be installed at each poletop switch installation. Operating mechanisms shall be solidly bonded to the ground with a flexible copper strap; joints in the operating mechanisms shall be flexible.

Ground rods shall be not less than 20 by 6000 millimeter 3/4-inch by 20-foot long copper-clad steel. Two rods at least 3000 millimeter 10 feet apart shall be [driven] [installed using a water jetting method] at each switch and shall be solidly bonded together and independently bonded to the switch.

-- End of Section --