
USACE / NAVFAC / AFCEA / NASA UFGS-26 09 23.00 40 (November 2008)

Preparing Activity: NASA Superseding
UFGS-26 09 23.00 40 (July 2007)

UNIFIED FACILITIES GUIDE SPECIFICATIONS

References are in agreement with UMRL dated January 2010

SECTION 26 09 23.00 40

LIGHTING CONTROL DEVICES 11/08

NOTE: This guide specification covers the requirements for [photoconductive][____]-lighting control devices for use with [interior] [exterior] lighting systems.

Edit this guide specification for project specific requirements by adding, deleting, or revising text. For bracketed items, choose applicable items(s) or insert appropriate information.

Remove information and requirements not required in respective project, whether or not brackets are present.

Comments and suggestions on this guide specification are welcome and should be directed to the technical proponent of the specification. A listing of technical proponents, including their organization designation and telephone number, is on the Internet.

Recommended changes to a UFGS should be submitted as a Criteria Change Request (CCR).

PART 1 GENERAL

1.1 REFERENCES

NOTE: This paragraph is used to list the publications cited in the text of the guide specification. The publications are referred to in the text by basic designation only and listed in this paragraph by organization, designation, date, and title.

Use the Reference Wizard's Check Reference feature when you add a RID outside of the Section's Reference Article to automatically place the reference in the Reference Article. Also use the Reference Wizard's Check Reference feature to update

the issue dates.

References not used in the text will automatically
be deleted from this section of the project
specification when you choose to reconcile
references in the publish print process.

The publications listed below form a part of this specification to the
extent referenced. The publications are referred to within the text by the
basic designation only.

GREEN SEAL (GS)

GC-12 (1997) Occupancy Sensors

ILLUMINATING ENGINEERING SOCIETY OF NORTH AMERICA (IESNA)

IESNA LM-48 (2001) Guide for Calibration of
Photoelectric Control Devices

NATIONAL ELECTRICAL MANUFACTURERS ASSOCIATION (NEMA)

NEMA C136.10 (2006) American National Standard for
Roadway Lighting Equipment-Locking-Type
Photocontrol Devices and Mating
Receptacles - Physical and Electrical
Interchangeability and Testing

NEMA ICS 1 (2000; R 2005; R 2008) Standard for
Industrial Control and Systems General
Requirements

NEMA ICS 2 (2000; R 2005; Errata 2008) Standard for
Industrial Control and Systems:
Controllers, Contactors, and Overload
Relays Rated Not More than 2000 Volts AC
or 750 Volts DC: Part 8 - Disconnect
Devices for Use in Industrial Control
Equipment

NEMA ICS 6 (1993; R 2006) Standard for Industrial
Controls and Systems Enclosures

UNDERWRITERS LABORATORIES (UL)

UL 20 (2000 ; Rev thru Dec 2008) Standard for
General-Use Snap Switches

UL 773 (1995; Rev thru Mar 2002) Standard for
Plug-In Locking Type Photocontrols for Use
with Area Lighting

UL 773A (2006) Nonindustrial Photoelectric
Switches for Lighting Control

UL 98 (2004; Rev thru Apr 2006) Enclosed and
Dead-Front Switches

1.2 GENERAL REQUIREMENTS

NOTE: If Section 26 00 00.00 20 BASIC ELECTRICAL MATERIALS AND METHODS is not included in the project specification, applicable requirements therefrom should be inserted and the following paragraph deleted.

Section 26 00 00.00 20 BASIC ELECTRICAL MATERIALS AND METHODS applies to work specified in this section.

Submit Installation Drawings for [light-sensitive] [occupancy sensitive] [motion sensitive] control devices in accordance with the manufacturer's recommended instructions for installation.

1.3 SUBMITTALS

NOTE: Review Submittal Description (SD) definitions in Section 01 33 00 SUBMITTAL PROCEDURES and edit the following list to reflect only the submittals required for the project. Keep submittals to the minimum required for adequate quality control.

A "G" following a submittal item indicates that the submittal requires Government approval. Some submittals are already marked with a "G". Only delete an existing "G" if the submittal item is not complex and can be reviewed through the Contractor's Quality Control system. Only add a "G" if the submittal is sufficiently important or complex in context of the project.

For submittals requiring Government approval on Army projects, a code of up to three characters within the submittal tags may be used following the "G" designation to indicate the approving authority. Codes for Army projects using the Resident Management System (RMS) are: "AE" for Architect-Engineer; "DO" for District Office (Engineering Division or other organization in the District Office); "AO" for Area Office; "RO" for Resident Office; and "PO" for Project Office. Codes following the "G" typically are not used for Navy, Air Force, and NASA projects.

Choose the first bracketed item for Navy, Air Force and NASA projects, or choose the second bracketed item for Army projects.

Government approval is required for submittals with a "G" designation; submittals not having a "G" designation are [for Contractor Quality Control approval.][for information only. When used, a designation following the "G" designation identifies the office that will review the submittal for the Government.] Submit the following in accordance with Section 01 33 00 SUBMITTAL PROCEDURES:

SD-03 Product Data

Submit manufacturer's catalog data for **Photoconductive Control Devices**.

Submit **Installation Drawings** for **Light-Sensitive Control Devices** in accordance with paragraph entitled, "General Requirements," of this section.

Dimming ballast controls[; G][; G, [_____]]

Light Level Sensor[; G][; G, [_____]]

Dimmer Switch[; G][; G, [_____]]

Lighting Contactor[; G][; G, [_____]]

Time Switch[; G][; G, [_____]]

Photocell Switch[; G][; G, [_____]]

Occupancy Sensors[; G][; G, [_____]]

Motion Sensors

SD-06 Test Reports

Submit test reports for **System Operation Tests** in the presence of the Contracting Officer.

SD-08 Manufacturer's Instructions

Submit operational instructions for **Light-Sensitive Control Devices** consisting of the manufacturer's recommended procedures for operation.

SD-10 Operation and Maintenance Data

NOTE: Require O&M manuals for lighting control systems that use low voltage control circuits.
Example: Light level sensors used with dimming ballast, occupancy, and motion sensors used with power packs.

Lighting Control System, Data Package 5[; G][; G, [_____]]

PART 2 PRODUCTS

2.1 PHOTOCONDUCTIVE CONTROL DEVICES

NOTE: If automatic control of luminaires is desired, give first consideration to photo-control. If both photo-control and remote manual override are required for the lighting system, use a central contactor and a single system photo-cell.

**Individual luminaire photo-control of security
lighting systems will not be used where a remote
manual override is required.**

Provide photoconductive control devices in accordance with [UL 773](#). Control lighting luminaires [in banks by a single photo-control element mounted within each bank.] [individually by photo-control elements mounted [on] [or] [adjacent to] the heads of the luminaires.][Mold housing for [light-sensitive control devices](#) from translucent butyrate or acrylic plastic materials and fasten to the base with screws.] Provide physically and electrically interchangeable light sensitive control devices with three-pole, 3-wire locking plug and receptacle connections to the line, load, and neutral conductors of the lighting circuit.

Provide photoconductive control devices for natural daylight and darkness control of incandescent, fluorescent, and [outdoor lighting](#) luminaires including a photoconductive cell, thermal actuator, and [snap-action switch in a weatherproof housing](#). Provide a control device which is, when attached to its mounting, weatherproof and constructed to exclude beating rain, snow, dust, and insects and capable of withstanding 96 percent relative humidity at 50 degrees C 122 degrees F for 48 hours under operating conditions.

Submit operation and maintenance data, [Lighting Control System, Data Package 5](#), in accordance with Section [01 78 23](#) OPERATION AND MAINTENANCE DATA and as specified herein, showing all light fixtures, control modules, control zones, occupancy sensors, [motion sensors](#), light level sensors, power packs, dimming ballasts, schematic diagrams and all interconnecting control wire, conduit, and associated hardware.

2.1.1 Photoconductive Limit Settings

Provide device which turns on within the limits of plus 100 to minus 50 percent of its setting, over a range of input voltage from 105 to 130 volts at rated frequency and ambient temperature, and at rated voltage and frequency over a range of temperature from minus 29 to 50 degrees C 85 to 122 degrees F, with relative humidities up to 96-percent throughout the temperature range.

Adjust the device to operate within the limits of 9 to 13 lux 0.8 to 1.2 foot-candles, but also capable of calibration of the turn-on light level over a minimum range from 5 to 32 lux 0.5 to 3.0 foot-candles, and adaptable for calibration up to 108 lux. 10 foot-candles. Ratio of turn-off light level to turn-on light level is not to exceed 5.

2.1.2 Device Rating and Accuracy

Rate the devices at 120 or 277 volts, 60 hertz, with rated ambient temperature of 25 plus or minus 5 degrees C 77 plus or minus 41 degrees F

Maintain instrument accuracy by proper calibration in accordance with [IESNA LM-48](#).

2.2 TIME CONTROL SWITCHES

**NOTE: If automatic control of luminaires is desired
and photo-control is not used, provide operation by**

timer control to ensure that luminaires come on automatically. Normally, the astronomic dial timer control switch is of the automatically wound spring mechanism type. A battery backed electronic switch capable of maintaining accurate time for 7 hours following a power failure may be substituted with the approval of the Contracting Officer.

Install switches with not less than four 6.4 mm 1/4 inch bolts. The use of sheet metal screws is not allowed.

[Provide with a time delay in excess of 5 seconds as an available option.
]

2.3 MANUAL AND SAFETY SWITCHES

NOTE: Delete NEMA ICS 6 enclosures when not required.

Provide Astronomic dial type arranged to turn "ON" at sunset, and turn "OFF" at a pre-determined time between [2030 hours] [_____] hours and [0230 hours] [_____] hours or sunrise, automatically changing the settings each day in accordance with seasonal changes of sunset and sunrise. Provide a switch rated [_____] volts, having [automatically wound spring mechanism] [battery backed electronic clock] to maintain accurate time for a minimum of 7 hours following a power failure, with a time switch with a manual on-off bypass switch. Provide surface mounted housing for the time switch, type NEMA [3R] [1 (indoor)] [4 (outdoor)] enclosure[conforming to NEMA ICS 6].

NOTE: Use manual switches for control of the lighting system when controls are located in a space that is continuously supervised, such as a guardhouse, gatehouse, or watchtower.

Provide switch mechanism consisting of a heavy-duty general-purpose precision snap-acting switch[, with NEMA ICS 6 Type [1] [4] enclosures,], single-pole, single-throw,[with a minimum rating of 1,000-watts incandescent-lamp load and 1,200-volt-amperes reactive for vapor-lamp load at rated voltage and frequency][suitable for operation on a [480Y/277] [208Y/120] [480] [277] [240] [120] volt, 60 Hz, [three-phase] [single-phase] system]. Provide with a selector switch having a minimum of three positions: ON, OFF, and AUTOMATIC. Use the automatic position when photoelectric or timer control is desired. Interface the selector switch with the lighting system magnetic contactor to control system activity.

Provide switches conforming to UL 98. Provide switch construction of the quick-make, quick-break type, such that a screwdriver is required to open the switch door when the switch is on, with blades visible when the door is open. Coordinate terminal lugs with the wire size.

[2.4 DIMMING BALLAST CONTROLS

The single slide dimming ballast control dimmer with on/off control, compatible with the ballast and control the ballast light output over the

full dimming range, which are approved by the ballast manufacturer.

2.5 LIGHT LEVEL SENSOR

Provide UL listed light level sensor capable of detecting changes in ambient lighting levels, with a dimming range of 20 percent to 100 percent, minimum, and designed for use with dimming ballast and voltage system to which they are connected. Provide with sensor capable of controlling 40 electronic dimming ballast, minimum, with a sensor light level adjustable with a set level range from 100 to 1000 lux 10 to 100 footcandles, minimum. Provide a sensor with a bypass function to electrically override sensor control.

2.6 INCANDESCENT DIMMER SWITCH

NOTE: Do not specify central dimming systems with
this specification.

UL 20, single-pole, [600][_____] watt, 120 volt ac, full-range rotary on-off type with built-in electromagnetic interference filter.

2.7 LIGHTING CONTACTOR

[Provide NEMA ICS 2,[electrically][mechanically] held contactor, rated [_____] volts, [_____] amperes, and [_____] poles, with coils rated [_____] volts.][Rate contactor as indicated.] Provide in NEMA[4][_____] enclosure conforming to NEMA ICS 6. Provide contactor with silver alloy double-break contacts [and coil clearing contacts for mechanically held contactor] requiring no arcing contacts.[Provide contactor with[hand-off-automatic][on-off] selector switch[.][, hermetically sealed.]]

2.8 TIME SWITCH

NOTE: Do not always use photocells and time switches together. Use the following information as a guide:

1. Lights on/lights off by photocell: Street parking lots. Any facility or street that requires lighting after dark.
2. Lights on by photocell; lights off by time switch: Most administration facilities, commissaries, hobby shops, or clubs. Any facility that does not stay open all night.
3. Lights on/lights off by time switch: Service stations, snack bars, barracks, or officers' quarters. Facilities that will be open to the public, or have personnel that report before daylight and after dark, but not continually through the night.
4. Other considerations: Time switches with a skip-a-day feature may be useful for facilities with a 5-day work week. (Program time switch to skip

Saturday and Sunday.) For facilities that do not stay open all night, it may be desirable to have lighting at night for security. Consult area Engineering Field Division for local station policy and exceptions to these procedures.

Provide astronomic dial type or electronic type, arranged to turn "ON" at sunset and turn "OFF" at predetermined time between 8:30 p.m. and 2:30 a.m. or sunrise, automatically changing the settings each day in accordance with seasonal changes of sunset and sunrise. Provide switch rated [_____] volts, having automatically wound spring mechanism or capacitor, to maintain accurate time for a minimum of 7 hours following power failure. Provide time switch with a manual on-off bypass switch. Surface mount the housing for the time switch, NEMA [3R][_____] enclosure conforming to NEMA ICS 6.

2.9 PHOTOCELL SWITCH

NOTE: Silicon diode type photocells are solid state devices and have limited sources. Therefore, cadmium-sulfide type cells cannot be deleted from the specification.

Provide photocell switch conforming to UL 773 or UL 773A, hermetically sealed cadmium-sulfide or silicon diode type cell rated [_____] volts ac, 60 Hz with[single-throw contacts][single pole double-throw (spdt) contacts for mechanically held contactors rated 1000 watts] designed to fail to the ON position. Provide switch which turns on at or below 32 lux 3 footcandles and off at 43 to 107 lux 4 to 10 footcandles. Provide time delay to prevent accidental switching from transient light sources.[Provide a directional lens in front of the cell to prevent fixed light sources from creating a turnoff condition.] Provide switch:

- [a. Integral to the luminaire, rated 1000W minimum.[Provide a directional lens in front of the cell to prevent fixed light sources from creating a turnoff condition.]]
- [b. In a U.V. stabilized polycarbonate housing with swivel arm and adjustable window slide, rated 1800 VA, minimum.]
- [c. In a high-impact-resistant, noncorroding and nonconductive molded plastic housing with a locking-type receptacle conforming to NEMA C136.10, rated 1800 VA, minimum.]
- [d. In a cast weatherproof aluminum housing with adjustable window slide, rated 1800 VA, minimum.]

2.10 OCCUPANCY SENSORS

NOTE: Occupancy sensors are useful in lighting control applications for private and open offices, restrooms, conference rooms, classrooms, utility areas, warehouses, and corridors. Additional design guidance can be found at the NAVFAC Criteria Office's website at:

"www.efdlant.navfac.navy.mil/criteria/documents/ITG/ITGLIST.asp".
Go to the "Interim Technical Guidance (ITG)" Article
on Occupant Sensors (1 JUL 96).

Also, most occupancy sensor manufacturers offer
design services for their products.

NOTE: Typical sensor applications are:
Ultrasonic - Restrooms, Hallways
Infrared - Warehouses, Open Offices
Combination Sensor - Classrooms, Conference Rooms

Provide UL listed occupancy sensor complying with GC-12. Design occupancy sensors and power packs to operate on the voltage indicated. Provide sensors and power packs with circuitry that only allows load switching at or near zero current crossing of supply voltage, with mounting as indicated. Provide sensor with an LED occupant detection indicator, adjustable sensitivity, and adjustable delayed-off time range of 5 minutes to 15 minutes. Provide[ivory][white][color matching the adjacent wall plates as specified in Section 26 20 00 INTERIOR DISTRIBUTION SYSTEM] wall mounted sensors, and white ceiling mounted sensors. Provide ceiling mounted sensors with 6.28 rad 360 degree coverage unless otherwise indicated.

- [a. Provide crystal controlled ultrasonic sensor which does not cause detection interference between adjacent sensors.]
- [b. Provide infrared sensors with a daylight filter, and a fresnel lens that is applicable to space to be controlled.]
- [c. Ultrasonic/Infrared Combination Sensor
- [d. Microwave and audiophonic sensors.]

Occupancy detection to turn lights on requires both ultrasonic and infrared sensor detection, such that the lights remain on if either the ultrasonic or infrared sensor detects movement. Provide infrared sensor with a lens selected for indicated usage and daylight filter to prevent short wavelength infrared interference. Provide crystal controlled ultrasonic sensor frequency.]

2.11 EQUIPMENT IDENTIFICATION

2.11.1 Manufacturer's Nameplate

Provide each item of equipment with a nameplate bearing the manufacturer's name, address, model number, and serial number securely affixed in an inconspicuous place; the nameplate of the distributing agent is not acceptable.

2.11.2 Labels

NOTE: Labeling of lighting components is an
inexpensive and effective method for helping
facilities personnel properly operate and maintain

the lighting systems. Use labels which are easy to read when standing next to the equipment, and durable to match the life of the equipment to which they are attached. Refer to the FEMP guidelines for lighting at

http://www.eere.energy.gov/femp/technologies/eep_lighting_guidance.cfm.

Provide labeled control devices, clearly marked for operation of specific lighting functions according to type. Note the following devices characteristics in the format "Use Only _____":

Make markings related to control device type clear and locate to be readily visible to service personnel, but unseen from normal viewing angles when devices are in place.

PART 3 EXECUTION

3.1 INSTALLATION

3.1.1 Photoconductive Control Devices

Install [photoconductive] [_____] control devices in accordance with the manufacturer's installation instructions.

3.1.2 Time Control Switches

Install switches with not less than four 6.4 mm 1/4 inch bolts. The use of sheet metal screws is not allowed.

3.1.3 Manual and Safety Switches

Coordinate terminal lugs with the wire size. Securely fasten switches to the supporting structure or wall using not less than four 6.4 mm 1/4 inch bolts. The use of sheet metal screws is not allowed.

3.1.4 Magnetic Contactors

NOTE: Use mechanically held, electrically operated magnetic contactors to control operation of the lighting system circuits.

Provide magnetic contactors mechanically held, electrically operated, conforming to NEMA ICS 1 and NEMA ICS 2, suitable for [480] [277] [240] [208] [120] volts, [single] [3] phase, 60 Hz, with coil voltage of [120] [277] [208] [240] volts. Provide with maximum continuous ampere rating and number of poles as indicated on drawings. Provide enclosures for contactors mounted indoors conforming to NEMA ICS 6, Type 1. Provide each contactor with a spare, normally open auxiliary contact.

Coordinate terminal lugs with the wire size. Securely fasten switches to the supporting structure or wall using not less than four 6.4 mm 1/4 inch bolts. The use of sheet metal screws is not allowed.

3.2 FIELD TESTING

Demonstrate that photoconductive control devices operate satisfactorily in the presence of the Contracting Officer.

Perform [System Operation Tests](#) in accordance with referenced standards in this section.

-- End of Section --