

the issue dates.

References not used in the text will automatically be deleted from this section of the project specification when you choose to reconcile references in the publish print process.

The publications listed below form a part of this specification to the extent referenced. The publications are referred to within the text by the basic designation only.

INSTITUTE OF ELECTRICAL AND ELECTRONICS ENGINEERS (IEEE)

- IEEE 242 (2001; Errata 2003) Recommended Practice for Protection and Coordination of Industrial and Commercial Power Systems - Buff Book
- IEEE 399 (1997) Brown Book IEEE Recommended Practice for Power Systems Analysis
- IEEE C37.40 (2003; Errata 2003; R 2009) Service Conditions & Definitions for High-Voltage Fuses, Distribution Enclosed Single-Pole Air Switches, Fuse Disconnecting Switches, & Accessories
- IEEE C37.41 (2008; Errata 2009) Standard Design Tests for High-Voltage (>1000 V) Fuses, Fuse and Disconnecting Cutouts, Distribution Enclosed Single-Pole Air Switches, Fuse Disconnecting Switches, and Accessories Used with These Devices
- IEEE C37.42 (2009) Standard Specifications for High-Voltage (> 1000 V) Expulsion-Type Distribution-Class Fuses, Fuse and Disconnecting Cutouts, Fuse Disconnecting Switches, and Fuse Links, and Accessories Used with These Devices
- IEEE C37.46 (2010) Standard for High Voltage Expulsion and Current-Limiting Type Power Class Fuses and Fuse Disconnecting Switches
- IEEE C37.47 (2000) Standard for High Voltage Current-Limiting Type Distribution Class Fuses and Fuse Disconnecting Switches

NATIONAL ELECTRICAL MANUFACTURERS ASSOCIATION (NEMA)

- NEMA ICS 3 (2005; R 2010) Medium-Voltage Controllers Rated 2001 to 7200 V AC
- NEMA ICS 6 (1993; R 2006) Enclosures
- NEMA SG 2 (1993) Standard for High-Voltage Fuses

NATIONAL FIRE PROTECTION ASSOCIATION (NFPA)

NFPA 70

(2011; TIA 11-1; Errata 2011) National
Electrical Code

1.2 SUBMITTALS

NOTE: Review Submittal Description (SD) definitions in Section 01 33 00 SUBMITTAL PROCEDURES and edit the following list to reflect only the submittals required for the project. Keep submittals to the minimum required for adequate quality control.

A "G" following a submittal item indicates that the submittal requires Government approval. Some submittals are already marked with a "G". Only delete an existing "G" if the submittal item is not complex and can be reviewed through the Contractor's Quality Control system. Only add a "G" if the submittal is sufficiently important or complex in context of the project.

For submittals requiring Government approval on Army projects, a code of up to three characters within the submittal tags may be used following the "G" designation to indicate the approving authority. Codes for Army projects using the Resident Management System (RMS) are: "AE" for Architect-Engineer; "DO" for District Office (Engineering Division or other organization in the District Office); "AO" for Area Office; "RO" for Resident Office; and "PO" for Project Office. Codes following the "G" typically are not used for Navy, Air Force, and NASA projects.

Choose the first bracketed item for Navy, Air Force and NASA projects, or choose the second bracketed item for Army projects.

Government approval is required for submittals with a "G" designation; submittals not having a "G" designation are [for Contractor Quality Control approval.] [for information only. When used, a designation following the "G" designation identifies the office that will review the submittal for the Government.] Submit the following in accordance with Section 01 33 00 SUBMITTAL PROCEDURES:

SD-02 Shop Drawings

Fabrication Drawings[; G][; G, [____]]

Installation Drawings[; G][; G, [____]]

SD-03 Product Data

Equipment and Performance Data[; G][; G, [____]]

Distribution Fuse Cutouts[; G][; G, [____]]

SD-07 Certificates

Testing[; G][; G, [_____]]

SD-08 Manufacturer's Instructions

Fuse Cutouts[; G][; G, [_____]]

Manufacturer's Installation Instructions[; G][; G, [_____]]

1.3 SYSTEM REQUIREMENTS

NOTE: If Section 26 00 00.00 20 BASIC ELECTRICAL MATERIALS AND METHODS is not included in the project specification, insert applicable requirements therefrom and delete the following paragraph.

[Section 26 00 00.00 20 BASIC ELECTRICAL MATERIALS AND METHODS applies to work specified in this section.
]

NOTE: Show the following information the drawings:

1. Conductor sizes, types, and materials.

2. Primary fused cutout; give voltage rating and state fusing (ampere rating) and "K" quick or "T" tardy required for coordination with existing upstream sectionalizing equipment.

Submit [fabrication drawings](#) for fuse cutouts consisting of fabrication and assembly details to be performed in the factory.

Submit [equipment and performance data](#) for [distribution fuse cutouts](#) including life, [testing](#) certificates verifying conformance to referenced standards, system functional flows, safety features, and mechanical automated details.

PART 2 PRODUCTS

2.1 EQUIPMENT STANDARDS

Ensure distribution fuse cutouts conform to the following requirements:

IEEE C37.40

IEEE C37.41

IEEE C37.42

IEEE C37.46

IEEE C37.47

IEEE 242

IEEE 399

NEMA ICS 3

NEMA ICS 6

NEMA SG 2

NFPA 70

2.2 FUSE CUTOUTS

Submit manufacturer's instructions for fuse cutouts including special provisions required to install equipment components and system packages. Include special notices detailing impedances, hazards and safety precautions.

Ensure distribution fuse cutouts are self-contained, enclosed, dropout type, or open type when required for higher voltage or interrupting rating. Install loadbreak cutouts only if specifically indicated.

Ensure the interrupting capacity is sufficient to break the maximum system fault current to which the cutout will be subjected. The minimum interrupting capacity is 16,000 amperes root mean square asymmetric.

Provide heavy-duty or extra-heavy-duty classification cutouts. Ensure cutouts installed on three-phase, 13.2-kilovolt (kV) or 13.8-kV systems are rated at 15 kV. The installation of cutouts rated at 7.8 kV on these systems is not allowed.

Provide fuse links with a continuous rating equal to approximately 150 percent of the full-load line current when used for transformer protection, and approximately [100] [110] [_____] percent of the conductor rated capacity when used for circuit protection. Ensure the 15-kV cutout has a wet withstand, 10-second voltage rating of 37 kV, with a 95-kV basic impulse level (BIL). Provide with a continuous current rating of 100 amperes unless otherwise indicated. Provide fuse disconnects rated not less than 100 amperes, having attachments to permit manual operation of the disconnect under load without external arcing.

Where indicated, combine lightning arresters and fuse cutouts.

PART 3 EXECUTION

3.1 INSTALLATION

Install distribution fuse cutouts in accordance [installation drawings](#) with the [manufacturer's installation instructions](#).

-- End of Section --