

For submittals requiring Government approval on Army projects, a code of up to three characters within the submittal tags may be used following the "G" designation to indicate the approving authority. Codes for Army projects using the Resident Management System (RMS) are: "AE" for Architect-Engineer; "DO" for District Office (Engineering Division or other organization in the District Office); "AO" for Area Office; "RO" for Resident Office; and "PO" for Project Office. Codes following the "G" typically are not used for Navy, Air Force, and NASA projects.

Choose the first bracketed item for Navy, Air Force and NASA projects, or choose the second bracketed item for Army projects.

Government approval is required for submittals with a "G" designation; submittals not having a "G" designation are [for Contractor Quality Control approval.] [for information only. When used, a designation following the "G" designation identifies the office that will review the submittal for the Government.] Submit the following in accordance with Section 01330 SUBMITTAL PROCEDURES:

SD-02 Shop Drawings

Fabrication Drawings shall be submitted in accordance with paragraph entitled, "General Requirements," of this section.

Installation Drawings shall be submitted in accordance with the paragraph entitled, "Installation," of this section.

SD-03 Product Data

Equipment and performance data shall be submitted for air-break disconnect switches including life, test, system functional flows, safety features, and mechanical automated details.

Manufacturer's catalog data shall be submitted for the following items:

Air-Break Disconnect Switches
Contacts
Handles
Hook Sticks

SD-08 Manufacturer's Instructions

Manufacturer's instructions shall be submitted for Air-Break Disconnect Switches including special provisions required to install equipment components and system packages. Special notices shall detail impedances, hazards and safety precautions.

SD-10 Operation and Maintenance Data

Operation and Maintenance Manuals shall be submitted for the following equipment:

Air-Break Disconnect Switches

1.3 GENERAL REQUIREMENTS

NOTE: If Section 16003S GENERAL ELECTRICAL PROVISIONS is not included in the project specification, applicable requirements therefrom should be inserted and the following paragraph deleted.

Section 16003S GENERAL ELECTRICAL PROVISIONS applies to work specified in this section.

Fabrication Drawings shall be submitted for air-break disconnect switches consisting of fabrication and assembly details to be performed in the factory.

PART 2 PRODUCTS

2.1 SWITCHES

Air-break disconnect switches shall be the types and ratings indicated and shall be provided complete, as an integral unit consisting of a galvanized channel base, insulators, contacts, live parts, and switch blade. Mechanism shall be the quick-break type. Switches may be three-phase, gang-operated, or single-pole, hook-stick-operated, as required by the application and installation requirements or as indicated. If motor-operated air-break switches are used, the installation shall be as indicated.

2.2 CONTACTS

Switch contacts shall be a self-cleaning design to prevent galling, and the switch blade shall have a positive latch to prevent accidental opening.

2.3 HANDLES

Operating handles of gang-operated switches shall be located approximately 1500 millimeter 5-feet above the ground and shall be provided with suitable attachments for padlocking the switches in both open and closed positions.

2.4 HOOK STICKS

NOTE: Operation & Maintenance organization may deem this sentence unnecessary.

One hook stick of suitable design and voltage rating shall be provided for each group of three single-pole hook-stick-operated switches.

PART 3 EXECUTION

3.1 INSTALLATION

Switches shall be mounted in accordance with the detailed instructions of

the manufacturer. Installation shall include necessary timbers, hardware, insulators, and connections to the line wire or bus.

Prior to final acceptance the switch shall be energized and the circuit loaded (to the maximum load possible, but not less than 10 percent of expected full load) for a minimum of 10 minutes and the temperature measured, with a non-contact device, to verify contact pressure and alignment. The temperature detector shall be accurate within 0.5 degrees C. Each phase temperature shall be less than 5 degrees C above ambient and within 3 C degrees of each other. Temperatures outside these values warrant investigation.

Installation Drawings shall be submitted for air-break switches.

3.2 GROUNDING

NOTE: In locations where existing underground
utilities, equipment or structures may be damaged,
ground rod installation should be accomplished using
the water jetting method.

Switches and operating mechanisms shall be solidly bonded to the station structural steel or to the ground counterpoise or driven ground rods; joints in the operating mechanisms shall be flexible.

-- End of Section --